Chapter 1

Multidimensional autoregression

The many applications of least squares to the one-dimensional convolution operator constitute the subject known as "**time-series analysis**." The ***autoregression*** filter, also known as the **prediction-error filter** (**PEF**), gathers statistics for us, not the autocorrelation or the spectrum directly but it gathers them indirectly as the inverse of the amplitude spectrum of its input. The PEF plays the role of the so-called "inverse-covariance matrix" in statistical estimation theory. Given the PEF, we use it to find missing portions of signals.

1.0.1 Time domain versus frequency domain

In the simplest applications, solutions can be most easily found in the frequency domain. When complications arise, it is better to use the time domain, to directly apply the convolution operator and the method of least squares.

A first complicating factor in the frequency domain is a required boundary in the time domain, such as that between past and future, or requirements that a filter be nonzero in a stated time interval. Another factor that attracts us to the time domain rather than the frequency domain is **weighting function**s.

Weighting functions are appropriate whenever a signal or image amplitude varies from place to place. Most of the literature on **time-series analysis** applies to the limited case of uniform weighting functions. Such time series are said to be "stationary." This means that their statistical properties do not change in time. In real life, particularly in the analysis of echos, signals are never stationary in time and space. A **stationarity** assumption is a reasonable starting assumption, but we should know how to go beyond it so we can take advantage of the many opportunities that do arise. In order of increasing difficulty in the frequency domain are the following complications:

1. A time boundary such as between past and future.

2. More time boundaries such as delimiting a filter.

3. More time boundaries such as erratic locations of missing data.
4. Nonstationary signal, i.e., time-variable weighting.
5. Time-axis stretching such as normal moveout.

We will not have difficulty with any of these complications here, because we will stay in the time domain and set up and solve optimization problems by use of the conjugate-direction method. Thus we will be able to cope with great complexity in goal formulation and get the right answer without approximations. By contrast, analytic or partly analytic methods can be more economical, but they generally solve somewhat different problems than those given to us by nature.

1.1 SOURCE WAVEFORM, MULTIPLE REFLECTIONS

Here we devise a simple mathematical model for deep **water bottom** multiple reflections.[1] There are two unknown waveforms, the source waveform $S(\omega)$ and the ocean-floor reflection $F(\omega)$. The water-bottom primary reflection $P(\omega)$ is the convolution of the source waveform with the water-bottom response; so $P(\omega) = S(\omega)F(\omega)$. The first multiple reflection $M(\omega)$ sees the same source waveform, the ocean floor, a minus one for the free surface, and the ocean floor again. Thus the observations $P(\omega)$ and $M(\omega)$ as functions of the physical parameters are

$$P(\omega) = S(\omega)\, F(\omega) \tag{1.1}$$
$$M(\omega) = -S(\omega)\, F(\omega)^2 \tag{1.2}$$

Algebraically the solutions of equations (1.1) and (1.2) are

$$F(\omega) = -M(\omega)/P(\omega) \tag{1.3}$$
$$S(\omega) = -P(\omega)^2/M(\omega) \tag{1.4}$$

These solutions can be computed in the Fourier domain by simple division. The difficulty is that the divisors in equations (1.3) and (1.4) can be zero, or small. This difficulty can be attacked by use of a positive number ϵ to **stabilize** it. For example, multiply equation (1.3) on top and bottom by $P'(\omega)$ and add $\epsilon > 0$ to the denominator. This gives

$$F(\omega) = -\frac{M(\omega)P'(\omega)}{P(\omega)P'(\omega)+\epsilon} \tag{1.5}$$

where $P'(\omega)$ is the complex conjugate of $P(\omega)$. Although the ϵ stabilization seems nice, it apparently produces a nonphysical model. For ϵ large or small, the time-domain response could turn out to be of much greater duration than is physically reasonable. This should not happen with perfect data, but in real life, data always has a limited spectral band of good quality.

[1] For this short course I am omitting here many interesting examples of multiple reflections shown in my 1992 book, PVI.

Functions that are rough in the frequency domain will be long in the time domain. This suggests making a short function in the time domain by local smoothing in the frequency domain. Let the notation $< \cdots >$ denote smoothing by local averaging. Thus, to specify filters whose time duration is not unreasonably long, we can revise equation (1.5) to

$$F(\omega) \quad = \quad - \frac{< M(\omega) P'(\omega) >}{< P(\omega) P'(\omega) + \epsilon >} \tag{1.6}$$

where it remains to specify the method and amount of smoothing. The goal of finding the filters $F(\omega)$ and $S(\omega)$ is to best model the multiple reflections so that they can be subtracted from the data, and thus enable us to see what primary reflections have been hidden by the multiples.

These frequency-duration difficulties do not arise in a time-domain formulation. Unlike in the frequency domain, in the time domain it is easy and natural to limit the duration and location of the nonzero time range of $F(\omega)$ and $S(\omega)$. First express (1.3) as

$$0 \quad = \quad P(\omega) F(\omega) + M(\omega) \tag{1.7}$$

To imagine equation (1.7) as a fitting goal in the time domain, instead of scalar functions of ω, think of vectors with components as a function of time. Thus $\mathbf{f}$ is a column vector containing the unknown sea-floor filter, $\mathbf{m}$ contains the "multiple" portion of a seismogram, and $\mathbf{P}$ is a matrix of down-shifted columns, each column being the "primary".

$$\mathbf{0} \quad \approx \quad \mathbf{r} \quad = \quad \begin{bmatrix} r_1 \\ r_2 \\ r_3 \\ r_4 \\ r_5 \\ r_6 \\ r_7 \\ r_8 \end{bmatrix} \quad = \quad \begin{bmatrix} p_1 & 0 & 0 \\ p_2 & p_1 & 0 \\ p_3 & p_2 & p_1 \\ p_4 & p_3 & p_2 \\ p_5 & p_4 & p_3 \\ p_6 & p_5 & p_4 \\ 0 & p_6 & p_5 \\ 0 & 0 & p_6 \end{bmatrix} \begin{bmatrix} f_1 \\ f_2 \\ f_3 \end{bmatrix} + \begin{bmatrix} m_1 \\ m_2 \\ m_3 \\ m_4 \\ m_5 \\ m_6 \\ m_7 \\ m_8 \end{bmatrix} \tag{1.8}$$

1.2 TIME-SERIES AUTOREGRESSION

Given y_t and y_{t-1}, you might like to predict y_{t+1}. The prediction could be a scaled sum or difference of y_t and y_{t-1}. This is called "**autoregression**" because a signal is regressed on itself. To find the scale factors you would optimize the fitting goal below, for the **prediction filter** (f_1, f_2):

$$\mathbf{0} \quad \approx \quad \mathbf{r} \quad = \quad \begin{bmatrix} y_1 & y_0 \\ y_2 & y_1 \\ y_3 & y_2 \\ y_4 & y_3 \\ y_5 & y_4 \end{bmatrix} \begin{bmatrix} f_1 \\ f_2 \end{bmatrix} - \begin{bmatrix} y_2 \\ y_3 \\ y_4 \\ y_5 \\ y_6 \end{bmatrix} \tag{1.9}$$

(In practice, of course the system of equations would be much taller, and perhaps somewhat wider.) A typical row in the matrix (1.9) says that $y_{t+1} \approx y_t f_1 + y_{t-1} f_2$ hence the description of f as a "prediction" filter. The error in the prediction is simply the residual. Define the residual to have opposite polarity and merge the column vector into the matrix, so you get

$$\begin{bmatrix} 0 \\ 0 \\ 0 \\ 0 \\ 0 \end{bmatrix} \quad \approx \quad \mathbf{r} \quad = \quad \begin{bmatrix} y_2 & y_1 & y_0 \\ y_3 & y_2 & y_1 \\ y_4 & y_3 & y_2 \\ y_5 & y_4 & y_3 \\ y_6 & y_5 & y_4 \end{bmatrix} \begin{bmatrix} 1 \\ -f_1 \\ -f_2 \end{bmatrix} \tag{1.10}$$

which is a standard form for autoregressions and prediction error.

Multiple reflections are predictable. It is the unpredictable part of a signal, the prediction residual, that contains the primary information. The output of the filter $(1, -f_1, -f_2) = (a_0, a_1, a_2)$ is the unpredictable part of the input. This filter is a simple example of a "prediction-error" (PE) filter. It is one member of a family of filters called "error filters."

The error-filter family are filters with one coefficient constrained to be unity and various other coefficients constrained to be zero. Otherwise, the filter coefficients are chosen to have minimum power output. Names for various error filters follow:

$(1, a_1, a_2, a_3, \cdots, a_n)$	**prediction-error (PE) filter**
$(1, 0, 0, a_3, a_4, \cdots, a_n)$	gapped PE filter with a gap
$(a_{-m}, \cdots, a_{-2}, a_{-1}, 1, a_1, a_2, a_3, \cdots, a_n)$	**interpolation-error (IE) filter**

We introduce a **free-mask matrix K** which "passes" the freely variable coefficients in the filter and "rejects" the constrained coefficients (which in this first example is merely the first coefficient $a_0 = 1$).

$$\mathbf{K} \quad = \quad \begin{bmatrix} 0 & . & . \\ . & 1 & . \\ . & . & 1 \end{bmatrix} \tag{1.11}$$

To compute a simple prediction error filter $\mathbf{a} = (1, a_1, a_2)$ with the CD method, we write (1.9) or (1.10) as

$$\mathbf{0} \quad \approx \quad \mathbf{r} \quad = \quad \begin{bmatrix} y_2 & y_1 & y_0 \\ y_3 & y_2 & y_1 \\ y_4 & y_3 & y_2 \\ y_5 & y_4 & y_3 \\ y_6 & y_5 & y_4 \end{bmatrix} \begin{bmatrix} 0 & \cdot & \cdot \\ \cdot & 1 & \cdot \\ \cdot & \cdot & 1 \end{bmatrix} \begin{bmatrix} 1 \\ a_1 \\ a_2 \end{bmatrix} + \begin{bmatrix} y_2 \\ y_3 \\ y_4 \\ y_5 \\ y_6 \end{bmatrix} \tag{1.12}$$

Let us move from this specific fitting goal to the general case. (Notice the similarity of the free-mask matrix **K** in this filter estimation problem with the free-mask matrix **J** in missing

data goal (**??**).) The fitting goal is,

$$\begin{aligned} \mathbf{0} &\approx \mathbf{Ya} && (1.13)\\ \mathbf{0} &\approx \mathbf{Y(I-K+K)a} && (1.14)\\ \mathbf{0} &\approx \mathbf{YKa+Y(I-K)a} && (1.15)\\ \mathbf{0} &\approx \mathbf{YKa+Ya}_0 && (1.16)\\ \mathbf{0} &\approx \mathbf{YKa+y} && (1.17)\\ \mathbf{0} \approx \mathbf{r} &= \mathbf{YKa+r}_0 && (1.18) \end{aligned}$$

which means we initialize the residual with $\mathbf{r}_0 = \mathbf{y}$. and then iterate with

$$\begin{aligned} \Delta\mathbf{a} &\longleftarrow \mathbf{K'Y'\,r} && (1.19)\\ \Delta\mathbf{r} &\longleftarrow \mathbf{YK}\,\Delta\mathbf{a} && (1.20) \end{aligned}$$

1.3 PREDICTION-ERROR FILTER OUTPUT IS WHITE

The relationship between spectrum and PEF

Knowledge of an autocorrelation function is equivalent to knowledge of a spectrum. The two are simply related by Fourier transform. A spectrum or an autocorrelation function encapsulates an important characteristic of a signal or an image. Generally the spectrum changes slowly from place to place although it could change rapidly. Of all the assumptions we could make to fill empty bins, one that people usually find easiest to agree with is that the spectrum should be the same in the empty-bin regions as where bins are filled. In practice we deal with neither the spectrum nor its autocorrelation but with a third object. This third object is easily transformed to the spectrum. This third object is the Prediction Error Filter (PEF). Its spectrum is inverse to the data spectrum.

Undoing convolution in nature

Prediction-error filtering is also called "**deconvolution**". This word goes back to very basic models and concepts. In this model one envisions a random white-spectrum excitation function **x** existing in nature, and this excitation function is somehow filtered by unknown natural processes, with a filter operator **B** producing an *output* **y** in nature that becomes the *input* **y** to our computer programs. This is sketched in Figure 1.1. Then we design a prediction-error



Figure 1.1: Flow of information from nature, to observation, into computer. mda-systems [NR]

filter **A** on **y**, which yields a white-spectrumed output residual **r**. Because **r** and **x** theoretically

have the same spectrum, the tantalizing prospect is that maybe **r** equals **x**, meaning that the PEF **A** has *deconvolved* the unknown convolution **B**.

Causal with causal inverse

Theoretically, a PEF is a causal filter with a causal inverse. This adds confidence to the likelihood that deconvolution of natural processes with a PEF might get the correct phase spectrum as well as the correct amplitude spectrum. Naturally, the PEF does not give the correct phase to an "all-pass" filter. That is a filter with a phase shift but a constant amplitude spectrum. (I think most migration operators are in this category.)

Theoretically we should be able to use a PEF in either convolution or polynomial division. There are some dangers though, mainly connected with dealing with data in small windows. Truncation phenomena might give us PEF estimates that are causal, but whose inverse is not, so they cannot be used in polynomial division. This is a lengthy topic in the classic literature. This old, fascinating subject is examined in my books, FGDP and PVI. A classic solution is one by John Parker Burg. We should revisit the Burg method in light of the helix.

PEF output tends to whiteness

The most important property of a **prediction-error filter** or **PEF** is that its output tends to a **white spectrum**. No matter what the input to this filter, its output tends to whiteness as the number of the coefficients $n \to \infty$ tends to infinity. Thus, the **PE filter** adapts itself to the input by absorbing all its **color**. This has important statistical implications and important geophysical implications.

Spectral estimation

The PEF's output being white leads to an important consequence: To specify a spectrum, we can give the spectrum (of an input) itself, give its autocorrelation, or give its PEF coefficients. Each is transformable to the other two. Indeed, an effective mechanism of spectral estimation, developed by John P. **Burg** and described in **FGDP**, is to compute a PE filter and look at the inverse of its spectrum.

Short windows

The power of a PE filter is that a short filter can often extinguish, and thereby represent, the information in a long resonant filter. If the input to the PE filter is a sinusoid, it is exactly predictable by a three-term recurrence relation, and all the color is absorbed by a three-term PE filter (see exercises). Burg's spectral estimation is especially effective in short windows.

Weathered layer resonance

That the output spectrum of a PE filter is **white** is also useful geophysically. Imagine the reverberation of the **soil** layer, highly variable from place to place, as the resonance between the surface and deeper consolidated rocks varies rapidly with surface location because of geologically recent fluvial activity. The spectral **color** of this erratic variation on surface-recorded seismograms is compensated for by a PE filter. Of course, we do not want PE-filtered seismograms to be white, but once they all have the same spectrum, it is easy to postfilter them to any desired spectrum.

1.3.1 PEF whiteness proof in 1-D

The basic idea of least-squares fitting is that the residual is orthogonal to the fitting functions. Applied to the PE filter, this idea means that the output of a PE filter is orthogonal to lagged inputs. The **orthogonality** applies only for lags in the past, because prediction knows only the past while it aims to the future. What we want to show is different, namely, that the output is uncorrelated with *itself* (as opposed to the input) for lags in *both* directions; hence the output spectrum is **white**.

In (1.21) are two separate and independent autoregressions, $\mathbf{0} \approx \mathbf{Y}_a\mathbf{a}$ for finding the filter $\mathbf{a}$, and $\mathbf{0} \approx \mathbf{Y}_b\mathbf{b}$ for finding the filter $\mathbf{b}$. Evidently, if the matrices were infinitely tall, or if the values in the columns of the matrices got small towards the top and bottom, we would find that $\mathbf{a} = \mathbf{b}$.

$$\mathbf{0} \approx \mathbf{r}_a = \begin{bmatrix} y_1 & 0 & 0 \\ y_2 & y_1 & 0 \\ y_3 & y_2 & y_1 \\ y_4 & y_3 & y_2 \\ y_5 & y_4 & y_3 \\ y_6 & y_5 & y_4 \\ y_7 & y_6 & y_5 \\ y_8 & y_7 & y_6 \end{bmatrix} \begin{bmatrix} 1 \\ a_1 \\ a_2 \end{bmatrix}; \qquad \mathbf{0} \approx \mathbf{r}_b = \begin{bmatrix} 0 & 0 & 0 \\ y_1 & 0 & 0 \\ y_2 & y_1 & 0 \\ y_3 & y_2 & y_1 \\ y_4 & y_3 & y_2 \\ y_5 & y_4 & y_3 \\ y_6 & y_5 & y_4 \\ y_7 & y_6 & y_5 \end{bmatrix} \begin{bmatrix} 1 \\ b_1 \\ b_2 \end{bmatrix} \tag{1.21}$$

When the energy $\mathbf{r}'\mathbf{r}$ of a residual has been minimized, the residual $\mathbf{r}$ is orthogonal to the fitting functions. For example, choosing a_2 to minimize $\mathbf{r}'\mathbf{r}$ gives $0 = \partial\mathbf{r}'\mathbf{r}/\partial a_2 = 2\mathbf{r}'\partial\mathbf{r}/\partial a_2$. This shows that $\mathbf{r}'$ is perpendicular to $\partial\mathbf{r}/\partial a_2$ which is the rightmost column of the $\mathbf{Y}_a$ matrix. Thus the vector $\mathbf{r}_a$ is orthogonal to all the columns in the $\mathbf{Y}_a$ matrix except the first (because we do not minimize with respect to a_0).

Our goal is a different theorem that is imprecise when applied to the three coefficient filters displayed in (1.21), but becomes valid as the filter length tends to infinity $\mathbf{a} = (1, a_1, a_2, a_3, \cdots)$ and the matrices become infinitely wide. Actually, all we require is that b_n tend to zero. This generally happens because as n increases, y_{t-n} becomes a weaker and weaker predictor of y_t.

The matrix $\mathbf{Y}_a$ contains all of the columns that are found in $\mathbf{Y}_b$ except the last (and the last one will turn out be irrelevant). This means that $\mathbf{r}_a$ is not only orthogonal to all of $\mathbf{Y}_a$'s columns

(except the first) but $\mathbf{r}_a$ is also orthogonal to all of $\mathbf{Y}_b$'s columns except the last. Although $\mathbf{r}_a$ isn't really perpendicular to the last column of $\mathbf{Y}_b$, it doesn't matter because that column has hardly any contribution to $\mathbf{r}_b$ since $|b_n| << 1$. Because $\mathbf{r}_a$ is (effectively) orthogonal to all the components of $\mathbf{r}_b$, $\mathbf{r}_a$ is also orthogonal to $\mathbf{r}_b$ itself. (For any $\mathbf{u}$ and $\mathbf{v}$, if $\mathbf{r}\cdot\mathbf{u}=0$ and $\mathbf{r}\cdot\mathbf{v}=0$ then $\mathbf{r}\cdot(\mathbf{u}+\mathbf{v})=0$).

In choosing the example of Figure (1.21), I have shifted the two fitting problems by one lag. We could draw the two problems again shifted by two lags, three lags, and more, and we would find that $\mathbf{r}_b$ and $\mathbf{r}_a$ are always orthogonal. Actually, $\mathbf{r}_b$ and $\mathbf{r}_a$ both contain the same signal $\mathbf{r}$ but time-shifted. The orthogonality at all shifts means that the autocorrelation of $\mathbf{r}$ vanishes at all lags. The autocorrelation does not vanish at zero lag, however, because $\mathbf{r}_a$ is not orthogonal to its first column (because we did not minimize with respect to a_0).

As we redraw $\mathbf{0} \approx \mathbf{r}_b = \mathbf{Y}_b\mathbf{b}$ for various lags, we may shift the columns only downward because shifting them upward would bring in the first column of $\mathbf{Y}_a$ and the residual $\mathbf{r}_a$ is not orthogonal to that. Thus we have only proven that one side of the autocorrelation of $\mathbf{r}$ vanishes. That is enough however, because autocorrelation functions are symmetric, so if one side vanishes, the other must also.

If $\mathbf{a}$ and $\mathbf{b}$ were two-sided filters like $(\cdots, b_{-2}, b_{-1}, 1, b_1, b_2, \cdots)$ the proof would break. If $\mathbf{b}$ were two-sided, $\mathbf{Y}_b$ would catch the nonorthogonal column of $\mathbf{Y}_a$. Not only is $\mathbf{r}_a$ not proven to be perpendicular to the first column of $\mathbf{Y}_a$, but it cannot be orthogonal to it because a signal cannot be orthogonal to itself.

The consequence of this theorem is that the convolution of $\mathbf{y}$ and $\mathbf{a}$ is white noise (its autocorrelation is an impulse function) and that means that $\mathbf{y}$ and $\mathbf{a}$ have mutually inverse spectrums. In other words, $\mathbf{a}$ captures a fundamental statistical aspect of $\mathbf{y}$. Where information is missing we can use the PEF to guess it.

My third book, PVI[2] has many examples[3] of one-dimensional deconvolution, both synthetic and on field data, including the `gap` parameter.

1.3.2 Simple dip filters

Convolution in two dimensions is just like convolution in one dimension except that convolution is done on two axes. The input and output data are planes of numbers and the filter is also a plane. A two-dimensional filter is a small plane of numbers that is convolved over a big data plane of numbers.

Suppose the data set is a collection of seismograms uniformly sampled in space. In other words, the data is numbers in a (t,x)-plane. For example, the following filter destroys any

[2]http://sepwww.stanford.edu/sep/prof/pvi/toc_html/index.html

[3]http://sepwww.stanford.edu/sep/prof/pvi/tsa/paper_html/node1.html

wavefront aligned along the direction of a line containing both the "+1" and the "−1".

$$\begin{matrix} -1 & \cdot \\ \cdot & \cdot \\ \cdot & 1 \end{matrix} \tag{1.22}$$

The next filter destroys a wave with a slope in the opposite direction:

$$\begin{matrix} \cdot & 1 \\ -1 & \cdot \end{matrix} \tag{1.23}$$

To convolve the above two filters, we can reverse either on (on both axes) and correlate them, so that you can get

$$\begin{matrix} \cdot & -1 & \cdot \\ 1 & \cdot & \cdot \\ \cdot & \cdot & 1 \\ \cdot & -1 & \cdot \end{matrix} \tag{1.24}$$

which destroys waves of both slopes.

A **two-dimensional filter** that can be a **dip-rejection filter** like (1.22) or (1.23) is

$$\begin{matrix} a & \cdot \\ b & \cdot \\ c & 1 \\ d & \cdot \\ e & \cdot \end{matrix} \tag{1.25}$$

where the coefficients (a,b,c,d,e) are to be estimated by least squares in order to minimize the power out of the filter. (In the filter table, the time axis runs vertically.)

Fitting the filter to two neighboring traces that are identical but for a time shift, we see that the filter coefficients (a,b,c,d,e) should turn out to be something like $(-1,0,0,0,0)$ or $(0,0,-.5,-.5,0)$, depending on the dip (stepout) of the data. But if the two channels are not fully coherent, we expect to see something like $(-.9,0,0,0,0)$ or $(0,0,-.4,-.4,0)$. To find filters such as (1.24), we adjust coefficients to minimize the power out of filter shapes, as in

$$\begin{matrix} v & a & \cdot \\ w & b & \cdot \\ x & c & 1 \\ y & d & \cdot \\ z & e & \cdot \end{matrix} \tag{1.26}$$

With 1-dimensional filters, we think mainly of power spectra, and with 2-dimensional filters we can think of temporal spectra and spatial spectra. What is new, however, is that in two dimensions we can think of dip spectra (which is when a 2-dimensional spectrum has a particularly common form, namely when energy organizes on radial lines in the (ω, k_x)-plane). As a short (three-term) 1-dimensional filter can devour a sinusoid, we have seen that simple 2-dimensional filters can devour a small number of dips.

1.3.3 PEF whiteness proof in 2-D

A well-known property (see FGDP or PVI) of a 1-D PEF is that its energy clusters immediately after the impulse at zero delay time. Applying this idea to the helix in Figure **??** on page ?? shows us that we can consider a 2-D PEF to be a small halfplane like (**??**) on page ?? with an impulse along a side. These shapes are what we see here in Figure 1.2.



Figure 1.2: A 2-D whitening filter template, and itself lagged. At output locations "A" and "B," the filter coefficient is constrained to be "1". When the semicircles are viewed as having infinite radius, the B filter is contained in the A filter. Because the output at A is orthogonal to all its inputs, which include all inputs of B, the output at A is orthogonal to the output of B. mda-whitepruf [ER]

Figure 1.2 shows the input plane with a 2-D filter on top of it at two possible locations. The filter shape is a semidisk, which you should imagine being of infinitely large radius. Notice that semidisk A includes all the points in B. The output of disk A will be shown to be orthogonal to the output of disk B. Conventional least squares theory says that the coefficients of the filter are designed so that the output of the filter is orthogonal to each of the inputs to that filter (except for the input under the "1," because any nonzero signal cannot be orthogonal to itself). Recall that if a given signal is orthogonal to each in a given group of signals, then the given signal is orthogonal to all linear combinations within that group. The output at B is a linear combination of members of its input group, which is included in the input group of A, which are already orthogonal to A. Therefore the output at B is orthogonal to the output at A. In summary,

residual	$\perp$	fitting function
output at A	$\perp$	each input to A
output at A	$\perp$	each input to B
output at A	$\perp$	linear combination of each input to B
output at A	$\perp$	output at B

The essential meaning is that a particular lag of the output **autocorrelation** function vanishes.

Study Figure 1.2 to see for what lags all the elements of the B filter are wholly contained in the A filter. These are the lags where we have shown the output autocorrelation to be vanishing. Notice another set of lags where we have proven nothing (where B is moved to the right of A). Autocorrelations are centrosymmetric, which means that the value at any lag is the same as the value at the negative of that lag, even in 2-D and 3-D where the lag is a vector quantity. Above we have shown that a halfplane of autocorrelation values vanishes. By the

centrosymmetry, the other half must vanish too. Thus the autocorrelation of the PEF output is an impulse function, so its 2-D spectrum is white.

The helix tells us why the proper filter form is not a square with the "1" on the corner. Before I discovered the helix, I understood it another way (that I learned from John P. Burg): For a spectrum to be white, *all* nonzero autocorrelation lags must be zero-valued. If the filter were a quarter-plane, then the symmetry of autocorrelations would only give us vanishing in another quarter, so there would be two remaining quarter-planes where the autocorrelation was not zero.

Fundamentally, the white-output theorem requires a one-dimensional ordering to the values in a plane or volume. The filter must contain a halfplane of values so that symmetry gives the other half.

You will notice some nonuniqueness. We could embed the helix with a 90° rotation in the original physical application. Besides the difference in side boundaries, the 2-D PEF would have a different orientation. Both PEFs should have an output that tends to whiteness as the filter is enlarged. It seems that we could design whitening autoregression filters for 45° rotations also, and we could also design them for hexagonal coordinate systems. In some physical problems, you might find the nonuniqueness unsettling. Does it mean the "final solution" is nonunique? Usually not, or not seriously so. Recall even in one dimension, the time reverse of a PEF has the same spectrum as the original PEF. When a PEF is used for regularizing a fitting problem, it is worth noticing that the quadratic form minimized is the PEF times its adjoint so the phase drops out. Likewise, a missing data restoration also amounts to minimizing a quadratic form so the phase again drops out.

1.3.4 Examples of modeling and deconvolving with a 2-D PEF

Here we examine elementary signal-processing applications of 2-D prediction-error filters (PEFs) on both everyday 2-D textures and on seismic data. Some of these textures are easily modeled with prediction-error filters (PEFs) while others are not. All figures used the same 10×10 filter shape. No attempt was made to optimize filter size or shape or any other parameters.

Results in Figures 1.3-1.9 are shown with various familiar textures on the left as training data sets. From these training data sets, a prediction-error filter (PEF) is estimated using module `pef` on page 19. The center frame is synthetic data made by deconvolving (polynomial division) random numbers by the estimated PEF. The right frame is the more familiar process, convolving the estimated PEF on the training data set.

Theoretically, the right frame tends towards a white spectrum. Earlier you could notice the filter size by knowing that the output was taken to be zero where the filter is only partially on the data. This was annoying on real data where we didn't want to throw away any data around the sides. Now the filtering is done without a call to the boundary module so we have typical helix wraparound.

Since a PEF tends to the inverse of the spectrum of its input, results similar to these could



Figure 1.3: Synthetic granite matches the training image quite well. The prediction error is spectrally white as theoretically expected but seems to outline the grains. mda-granite [ER]



Figure 1.4: Synthetic wood grain has too little white. This is because of the nonsymmetric brightness histogram of natural wood. Again, the PEF output looks random as expected. mda-wood [ER]



Figure 1.5: A banker's suit (left). A student's suit (center). My suit (right). mda-herr [ER]



Figure 1.6: Basket weave. The synthetic data fails to segregate the two dips into a checkerboard pattern. The PEF output looks structured perhaps because the filter is too small. mda-basket [ER]



Figure 1.7: Brick. Synthetic brick edges are everywhere and do not enclose blocks containing a fixed color. PEF output highlights the mortar. mda-brick [ER]



Figure 1.8: Ridges. A spectacular failure of the stationarity assumption. All dips are present but in different locations. The ridges have been sharpened by the deconvolution. We cannot explain why the nonsymmetric ridges have become symmetric. mda-ridges [ER]



Figure 1.9: Gulf of Mexico seismic section, modeled, and deconvolved. Strong horizontal layering has been suppressed giving a better view of the hyperbolas. Do you see any prospects in the synthetic data? The decon filter is the same 10×10 used on the everyday textures. mda-WGstack [ER]

probably be found using Fourier transforms, smoothing spectra, etc. We used PEFs because of their flexibility. The filters can be any shape. They can dodge around missing data, or we can use them to estimate missing data. We avoid periodic boundary assumptions inherent to FT. The PEF's are designed only internal to known data, not off edges so they are readily adaptible to nonstationarity. Thinking of these textures as seismic time slices, the textures could easily be required to pass thru specific values at well locations.

1.4 PEF ESTIMATION WITH MISSING DATA

If we are not careful, our calculation of the PEF could have the pitfall that it would try to use the missing data to find the PEF, and hence it would get the wrong PEF. To avoid this pitfall, imagine a PEF finder that uses weighted least squares where the weighting function vanishes on those fitting equations that involve missing data. The weighting would be unity elsewhere. Instead of weighting bad results by zero, we simply will not compute them. The residual there will be initialized to zero and never changed. Likewise for the adjoint, these components of the residual will never contribute to a gradient. Module `hconest` assumes it knows the bad locations (where outputs are dependent on unknown inputs) and ignores computation there.

```
module hconest {              # masked helix convolution, adjoint is the filter.
use helix
```

```
  real, dimension (:), pointer :: x
  type( filter)                :: aa
#% _init( x, aa)
#% _lop( a, y)
    integer  ia, ix, iy
    do ia = 1, size( a) {
         do iy = 1  + aa%lag( ia), size( y) {    if( aa%mis( iy)) cycle
            ix = iy - aa%lag( ia)
             if( adj)    a( ia) +=  y( iy) * x( ix)
             else        y( iy) +=  a( ia) * x( ix)
         }
    }
}
```

Suppose that y_4 were a missing or a bad data value in the fitting goal (1.27). That would spoil the 4th, 5th and 6th fitting equations. Thus we would want to be sure that w_4, w_5, and w_6 were zero.

$$\mathbf{0} \approx \mathbf{Wr} = \begin{bmatrix} w_1 & . & . & . & . & . & . & . \\ . & w_2 & . & . & . & . & . & . \\ . & . & w_3 & . & . & . & . & . \\ . & . & . & w_4 & . & . & . & . \\ . & . & . & . & w_5 & . & . & . \\ . & . & . & . & . & w_6 & . & . \\ . & . & . & . & . & . & w_7 & . \\ . & . & . & . & . & . & . & w_8 \end{bmatrix} \begin{bmatrix} y_1 & 0 & 0 \\ y_2 & y_1 & 0 \\ y_3 & y_2 & y_1 \\ y_4 & y_3 & y_2 \\ y_5 & y_4 & y_3 \\ y_6 & y_5 & y_4 \\ 0 & y_6 & y_5 \\ 0 & 0 & y_6 \end{bmatrix} \begin{bmatrix} 1 \\ a_1 \\ a_2 \end{bmatrix} \tag{1.27}$$

When missing y_i are sprinkled around, which of the w_i should vanish? A simple solution (that we cannot use) is to put zeros in place of missing data and then take the product of every element in a row of the $\mathbf{Y}$ matrix. The product will vanish if any element in the row vanishes. We cannot use this solution because it would require us to have the matrix, when actually we have only an operator, a program that applies the matrix. A feasible solution uses complementary logic: We prepare a template like $\mathbf{y}$ with ones where data is missing and zeros where the data is known. We prepare a template like $\mathbf{a}$ where all values are ones. We put the templates themselves into (1.27) and apply the operator. Where the outputs are nonzero we have defective fitting equations and that is where we want the weights to be zero. It is all done in module `misinput` on the current page.

```
module misinput {                       # find a mask of missing filter inputs
  use helicon
contains
  subroutine find_mask( known, aa) {
    logical,  intent( in)          :: known(:)
    type( filter)                  :: aa
    real, dimension( size (known)) :: rr, dfre
    integer                        :: stat
    where( known) dfre = 0.
    elsewhere     dfre = 1.
    call helicon_init( aa)
    aa%flt = 1.
```

```
    stat = helicon_lop( .false., .false., dfre, rr)
    aa%flt = 0.
    where ( rr > 0.)   aa%mis = .true.
    }
}
```

EXERCISES:

1 The Galilee data set is a collection of tracks that can be put on a regular mesh using the linear interpolation operator $\mathbf{0} \approx \mathbf{Lm} - \mathbf{d}$ along with some regularization. We observe that some of the tracks have different mean values than others which show up in our previous images. The tracks themselves are not clearly demarked in the data. We can eliminate the mean and suppress low frequency trends if we filter the residual with a simple low cut filter. The simplest thing is the derivative along the track. Call this $\frac{\partial}{\partial s}$. This gives the fitting goal $\mathbf{0} \approx \frac{\partial}{\partial s}(\mathbf{Lm} - \mathbf{d})$. Since $\frac{\partial}{\partial s}$ is a filter, a one-dimensional gradient, we should not apply it to missing data. For this survey we have not so much missing data, but some erratic data: data outside the lake, water bottoms above the water surface, and simple bursts. Processing the depth $z(s)$ with the gradient $\frac{\partial}{\partial s}$ introduces new problems where we hit a spike or where one of the unmarked tracks ends and another begins. Fortunately, the original data has gone thru a preliminary examination identifying where many of the suspicious points lie. The original triples, (x_s, y_s, z_s) have been supplemented by a weighting function (x_s, y_s, z_s, w_s) that vanishes at the suspicious locations. (If I did this, I cannot find it now. The tool `Suspicious.rst` in `jon/res/mad` should be helpful.) What you are supposed to do is consider the suspicious points to be missing data values. Use knowledge of them with module `misinput` on the preceding page to design a filter, the one-dimensional gradient along the track. Choose suitable regularization. The result should be a track-free map of the lake. If the suspicious data points were all found by the pre-editor, the spikes should be gone too. Another description of this problem is at `http://sepwww.stanford.edu/sep/jon/trash/mad/`

1.4.1 Internal boundaries to multidimensional convolution

Sometimes we deal with small patches of data. In order that boundary phenomena not dominate the calculation intended in the central region, we need to take care that input data is not assumed to be zero beyond the interval that the data is given.

The two little triangular patches of zeros in the convolution matrix in equation (1.27) describe end conditions where it is assumed that the data y_t vanishes before $t = 1$ and after $t = 6$. Alternately we might not wish to make that assumption. Thus the triangles filled with zeros could be regarded as missing data. In this one-dimensional example, it is easy to see that the filter, say `yy%mis()` should be set to `.TRUE.` at the ends so no output would ever be computed there. We would like to find a general multidimensional algorithm to correctly specify `yy%mis()` around the multidimensional boundaries. This proceeds like the missing data algorithm, i.e. we apply a filter of all ones to a data space template that is taken all zeros

except ones at the locations of missing data, in this case y_0, y_{-1} and y_7, y_8. This amounts to surrounding the original data set with some missing data. We need padding the size of the filter on all sides. The padded region would be filled with ones (designating missing inputs). Where the convolution output is nonzero, there `yy%mis()` is set to `.TRUE.` denoting an output with missing inputs.

The two-dimensional case is a little more cluttered than the 1-D case but the principle is about the same. Figure 1.10 shows a larger input domain, a 5×3 filter, and a smaller output domain. There are two things to notice. First, sliding the filter everywhere inside the outer



Figure 1.10: Domain of inputs and outputs of a two-dimensional filter like a PEF. mda-rabdomain [NR]

box, we get outputs (under the 1 location) only in the inner box. Second, (the adjoint idea) crosscorrelating the inner and outer boxes gives us the 3×5 patch of information we use to build the filter coefficients. We need to be careful not to assume that signals vanish outside the region where they are defined. In a later chapter we will break data spaces into overlapping patches, separately analyze the patches, and put everything back together. We do this because crosscorrelations change with time and they are handled as constant in short time windows. There we must be particularly careful that zero signal values not be presumed outside of the small volumes; otherwise the many edges and faces of the many small volumes can overwhelm the interior that we want to study.

In practice, the input and output are allocated equal memory, but the output residual is initialized to zero everywhere and then not computed except where shown in figure 1.10. Below is module `bound` to build a selector for filter outputs that should never be examined or even computed (because they need input data from outside the given data space). Inputs are a filter `aa` and the size of its cube `na = (na(1),na(2),...)`. Also input are two cube dimensions, that of the data last used by the filter `nold` and that of the filter's next intended use `nd`. (`nold` and `nd` are often the same). Module `bound` begins by defining a bigger data space with room for a filter surrounding the original data space `nd` on all sides. It does this by the line `nb=nd+2*na`. Then we allocate two data spaces `xx` and `yy` of the bigger size `nb` and pack many ones in a frame of width `na` around the outside of `xx`. The filter `aa` is also filled with ones. The filter `aa` must be regridded for the bigger `nb` data space (regridding merely changes the lag values of the ones). Now we filter the input `xx` with `aa` getting `yy`. Wherever the output is nonzero, we have an output that has been affected by the boundary. Such an output should not be computed. Thus we allocate the logical mask `aa%mis` (a part of the helix filter definition in module `helix` on page ??) and wherever we see a nonzero value of `yy` in the output, we designate the output as depending on missing inputs by setting `aa%mis` to `.true.`.

```
module bound {          # mark helix filter outputs where input is off data.
use cartesian
use helicon
use regrid
contains
  subroutine boundn ( nold, nd, na, aa) {
    integer, dimension( :), intent( in) :: nold, nd, na     # (ndim)
    type( filter)                       :: aa
    integer, dimension( size( nd))      :: nb, ii
    real,    dimension( :), allocatable :: xx, yy
    integer                             :: iy, my, ib, mb, stat
    nb = nd + 2*na;   mb = product( nb)      # nb is a bigger space to pad into.
    allocate( xx( mb), yy( mb))              # two large spaces, equal size
    xx = 0.                                  #              zeros
    do ib = 1, mb {                          # surround the zeros with many ones
       call line2cart( nb, ib, ii)           # ii( ib)
       if( any( ii <= na  .or.  ii > nb-na))   xx( ib) = 1.
       }
    call helicon_init( aa)                   # give aa pointer to helicon.lop
    call regridn( nold, nb, aa);  aa%flt = 1.           # put all 1's in filter
    stat = helicon_lop( .false., .false., xx, yy)       # apply filter
    call regridn(   nb, nd, aa);  aa%flt = 0.    # remake filter for orig data.
    my = product( nd)
    allocate( aa%mis( my))              # attach missing designation to y_filter
    do iy = 1, my {                     # map from unpadded to padded space
       call line2cart( nd, iy, ii )
       call cart2line( nb,     ii+na, ib )          # ib( iy)
       aa%mis( iy) =             ( yy( ib) > 0.)    # true where inputs missing
       }
    deallocate( xx, yy)
    }
}
```

In reality one would set up the boundary conditions with module `bound` before identifying locations of missing data with module `misinput`. Both modules are based on the same concept, but the boundaries are more cluttered and confusing which is why we examined them later.

1.4.2 Finding the prediction-error filter

The first stage of the least-squares estimation is computing the **prediction-error filter**. The second stage will be using it to find the missing data. The input data space contains a mixture of known data values and missing unknown ones. For the first stage of finding the filter, we generally have many more fitting equations than we need so we can proceed by ignoring the fitting equations that involve missing data values. We ignore them everywhere that the missing inputs hit the filter.

The codes here do not address the difficulty that maybe too much data is missing so that all weights are zero. To add stabilization we could supplement the data volume with a synthetic "training dataset" or by a "prior filter". With things as they are, if there is not enough data

to specify a prediction-error filter, you should encounter the error exit from `cgstep()` on page ??.

```
module pef {              # Find prediction-error filter (helix magic)
  use hconest
  use cgstep_mod
  use solver_mod
contains
  subroutine find_pef( dd, aa, niter) {
    integer,          intent( in)  :: niter        # number of iterations
    type( filter)                  :: aa           # filter
    real,    dimension(:), pointer :: dd           # input data
    call hconest_init( dd, aa)
    call solver( hconest_lop, cgstep, aa%flt, -dd, niter, x0= aa%flt)
    call cgstep_close()
    }
}
```

Results are shown in Figures 1.11- 1.13. Here again, the PEF is carefully designed using module `bound` on page 17 so that no filter outputs are used where the filter is only partway on the data. After the PEF was designed, it is applied with the more cavalier helix treatment of boundaries so although you cannot see the frame of excluded outputs, you can see what happens as the filter is climbing onto the data.



Figure 1.11: Hole in wood. mda-wood-hole [ER]



Figure 1.12: Hole in herringbone. mda-herr-hole [ER]



Figure 1.13: Hole in brick. mda-brick-hole [ER]

1.5 TWO-STAGE LINEAR LEAST SQUARES

In Chapter **??** and Chapter **??** we filled empty bins by minimizing the energy output from the filtered mesh. In each case there was arbitrariness in the choice of the filter. Here we find and use the optimum filter, the PEF.

The first stage is that of the previous section, finding the optimal PEF while carefully avoiding using any regression equations that involve boundaries or missing data. For the second stage, we take the PEF as known and find values for the empty bins so that the power out of the prediction-error filter is minimized. To do this we find missing data with module `mis2()` on page ??.

This two-stage method avoids the nonlinear problem we would otherwise face if we included the fitting equations containing both free data values and free filter values. Presumably, after two stages of linear least squares we are close enough to the final solution that we could switch over to the full nonlinear setup described near the end of this chapter.

The synthetic data in Figure 1.14 is a superposition of two plane waves of different directions, each with a random (but low-passed) waveform. After punching a hole in the data, we find that the lost data is pleasingly restored, though a bit weak near the side boundary. This imperfection could result from the side-boundary behavior of the operator or from an insufficient number of missing-data iterations.

The residual selector in Figure 1.14 shows where the filter output has valid inputs. From it you can deduce the size and shape of the filter, namely that it matches up with Figure 1.10. The ellipsoidal hole in the residual selector is larger than that in the data because we lose regression equations not only at the hole, but where any part of the filter overlaps the hole.

The results in Figure 1.14 are essentially perfect representing the fact that that synthetic example fits the conceptual model perfectly. Figures 1.15-1.18 show real data of various kinds.



Figure 1.14: Original data (left), with a zeroed hole, restored, residual selector (right). mda-hole90 [ER,M]



Figure 1.15: The herringbone texture is a patchwork of two textures. We notice that data missing from the hole tends to fill with the texture at the edge of the hole. The spine of the herring fish, however, is not modeled at all. mda-herr-hole-fill [ER,M]

Figure 1.16: The brick texture has a mortar part (both vertical and horizontal joins) and a brick surface part. These three parts enter the empty area but do not end where they should. mda-brick-hole-fill [ER,M]



Figure 1.17: The theoretical model is a poor fit to the ridge data since the prediction must try to match ridges of all possible orientations. This data requires a broader theory which incorporates the possibility of nonstationarity (space variable slope). mda-ridges-hole-fill [ER,M]



Figure 1.18: Filling the missing seismic data. The imaging process known as "migration" would suffer diffraction artifacts in the gapped data that it would not suffer on the restored data. mda-WGstack-hole-fill [ER,M]

1.5.1 Infill of 3-D seismic data from a quarry blast

Finding **missing data** (filling empty bins) requires use of a filter. Because of the helix, the codes work in spaces of all dimensions.

An open question is how many conjugate-direction iterations are needed in missing-data programs. When estimating filters, I set the **iteration count** `niter` at the number of free filter parameters. Theoretically, this gives me the exact solution but sometimes I run double the number of iterations to be sure. The missing-data estimation, however is a completely different story. The number of free parameters in the missing-data estimation, could be very large. This often implies impractically long compute times for the exact solution. In practice I experiment carefully with `niter` and hope for the best. I find that where gaps are small, they fill in quickly. Where the gaps are large, they don't, and more iterations are required. Where the gaps are large is where we must experiment with preconditioning.

Figure 1.19 shows an example of replacing missing data by values predicted from a 3-D PEF. The data was recorded at **Stanford University** with a 13×13 array of independent recorders. The figure shows 12 of the 13 lines each of length 13. Our main goal was to measure the ambient night-time noise. By morning about half the recorders had dead batteries but the other half recorded a wave from a quarry blast. The raw data was distracting to look at because of the many missing traces so I interpolated it with a small 3-D filter. That filter was a PEF.



Figure 1.19: The left 12 panels are the inputs. The right 12 panels are outputs. mda-passfill90 [ER,M]

1.5.2 Imposing prior knowledge of symmetry

Reversing a signal in time does not change its autocorrelation. In the analysis of stationary time series, it is well known (**FGDP**) that the filter for predicting forward in time should be the same as that for "predicting" backward in time (except for time reversal). When the data samples are short, however, a different filter may be found for predicting forward than for backward. Rather than average the two filters directly, the better procedure is to find the filter that minimizes the sum of power in two residuals. One is a filtering of the original signal, and the other is a filtering of a time-reversed signal, as in equation (1.28), where the top half of the equations represent prediction-error predicting forward in time and the second half is prediction backward.

$$\begin{bmatrix} r_1 \\ r_2 \\ r_3 \\ r_4 \\ \hline r_5 \\ r_6 \\ r_7 \\ r_8 \end{bmatrix} = \begin{bmatrix} y_3 & y_2 & y_1 \\ y_4 & y_3 & y_2 \\ y_5 & y_4 & y_3 \\ y_6 & y_5 & y_4 \\ \hline y_1 & y_2 & y_3 \\ y_2 & y_3 & y_4 \\ y_3 & y_4 & y_5 \\ y_4 & y_5 & y_6 \end{bmatrix} \begin{bmatrix} 1 \\ a_1 \\ a_2 \end{bmatrix} \tag{1.28}$$

To get the bottom rows from the top rows, we simply reverse the order of all the components within each row. That reverses the input time function. (Reversing the order within a column would reverse the output time function.) Instead of the matrix being diagonals tipping 45° to the right, they tip to the left.

In an (x, y) space, you might also expect rotational symmetry. In an (x, t) space, dips are preserved if t-axis reversal is accompanied by x-axis reversal. Many of my research codes include these symmetries, but I excluded them here. Nowhere did I see that the reversal symmetry made noticable difference, but in coding, it always made noticeable clutter, expanding the residual to a two-component *residual array*.

Where a data sample grows exponentially towards the boundary, I expect that extrapolated data would diverge too. You can force it to go to zero (or any specified value) at some distance from the body of the known data. To do so, surround the body of data by missing data and surround that by specification of enough zeros. Enough is defined by the filter length.

1.5.3 Hexagonal coordinates

Suppose you acquire data on a hexagonal mesh as below



and some of the data values are missing. How can we apply the methods of this chapter? The solution is to append the given data by more missing data shown by the commas below.



Now we have a familiar two-dimensional coordinate system in which we can find missing values, as well as perform signal and noise separations as described in a later chapter.

1.6 SEABEAM: FILLING THE EMPTY BINS WITH A PEF

Recall the Seabeam data of Figure **??**. In chapter **??** we filled empty bins minimizing the output of Laplace's operator, getting Figure **??**.

The problem with the Laplacian operator as an interpolator is that it smears information uniformly in all directions. From Figure **??** we see that we need an anisotropic interpolation oriented along the regional trends. What we need is a PEF in place of the Laplacian. To get it, we apply module `pef` on page 19. After binning the data and finding this PEF, we do a second stage of linear-least-squares optimization with `mis2` on page ??, as we did for Figure 1.14, and we obtain the pleasing result in Figure 1.20.



Figure 1.20: Depth of the ocean interpolated with a PEF. mda-seapef90 [ER,M]

1.7 GEOSTATISTICS

Figures 1.21 and 1.22 show synthetic and real surveys containing regions where no data was recorded. The PEF method of this book produces the extrapolated image in the upper right. Notice that far from known data, the extrapolated data is weak. This is a result of a "minimum variance" calculation. Notice the weak interpolated data also has a different spectrum than the known data. It lacks the short wavelength fuzz. That's because the short wavelengths cannot be extrapolated long distances.

There is a simple way to acquire short wavelength fuzz at long distances by adding random fuzz of the proper spatial spectrum. This is what they do in Geostatistics. We can also do it within the usual geophysical estimation framework. Here is how we do it. Given the usual data fitting and model styling goals

$$\mathbf{0} \approx \mathbf{Lm} - \mathbf{d} \tag{1.29}$$

$$\mathbf{0} \approx \mathbf{Am} \tag{1.30}$$

We introduce a sample of random noise $\mathbf{n}$ and fit instead these regressions

$$\mathbf{0} \approx \mathbf{Lm} - \mathbf{d} \tag{1.31}$$

$$\mathbf{n} \approx \mathbf{Am} \tag{1.32}$$

Of course you get a different solution for each different realization of the random noise. You also need to be a little careful to use noise $\mathbf{n}$ of the correct variance. Bob Clapp (thesis) worked out the correct scalar variance. The wood image gives us the example in Figure 1.21. Figure 1.22 shows the same concept with the seabeam data.



Figure 1.21: Top left is wood with a hole punched out. Top right the hole filled with a PEF. The bottom two are realizations with different samples of noise **n**. Notice they differ inside the hole. mda-manywood [ER,M]

1.8 BOTH MISSING DATA AND UNKNOWN FILTER

Recall the missing-data figures beginning with Figure **??**. There the filters were taken as known, and the only unknowns were the missing data. Now, instead of having a predetermined filter, we will solve for the filter along with the missing data. The principle we will use is that the output power is minimized while the filter is constrained to have one nonzero coefficient (else all the coefficients would go to zero). We will look first at some results and then see how they were found.

In Figure 1.23 the filter is constrained to be of the form $(1, a_1, a_2)$. The result is pleasing in that the interpolated traces have the same general character as the given values. The filter came out slightly different from the $(1, 0, -1)$ that I guessed and tried in Figure **??**. Curiously, constraining the filter to be of the form $(a_{-2}, a_{-1}, 1)$ in Figure 1.24 yields the same interpolated missing data as in Figure 1.23. I understand that the sum squared of the coefficients of $A(Z)P(Z)$ is the same as that of $A(1/Z)P(Z)$, but I do not see why that would imply the same interpolated data; never the less, it seems to.

1.8.1 Objections to interpolation error

In any data interpolation or extrapolation, we want the extended data to behave like the original data. And, in regions where there is no observed data, the extrapolated data should drop away in a fashion consistent with its **spectrum** determined from the known region.



Figure 1.22: Top left is binned data. Top right extends the data with a PEF. The bottom two panels add appropriately colored random noise in the regions of missing data. (Bob Clapp) mda-bobsea [ER,M]



Figure 1.23: Top is known data. Middle includes the interpolated values. Bottom is the filter with the leftmost point constrained to be unity and other points chosen to minimize output power. mda-misif90 [ER]



Figure 1.24: The filter here had its rightmost point constrained to be unity—i.e., this filtering amounts to backward prediction. The interpolated data seems to be identical to that of forward prediction. mda-backwards90 [ER]

My basic idea is that the spectrum of the missing data should match that of the known data. This is is the idea that the spectrum should be unchanging from a known region to an unknown region. A technical word to express the idea of spectra not changing is "**stationary**." This happens with the PEF (one-sided filter) because its spectrum tends to the inverse of that of the known data while that of the unknown data tends to the inverse of that of the PEF. Thus the spectrum of the missing data is the "inverse of the inverse" of the spectrum of the known. The PEF enables us to fill in the missing area with the spectral shape of the known area. (In regions far away or unpredictable, the spectral shape may be the same, but the energy drops to zero.)

On the other hand, the **interpolation-error filter**, a filter like $(a_{-2}, a_{-1}, 1, a_1, a_2)$, should fail to do the job because it has the wrong spectrum. Its spectrum tends to the inverse of the input spectrum (I am stating this fact without proof), so the spectrum of the IE filter tends to the inverse *squared* of the input spectrum.

To confirm and show these concepts, I prepared synthetic data consisting of a fragment of a damped exponential, and off to one side of it an impulse function. Most of the energy is in the damped exponential. Figure 1.25 shows that the spectrum and the extended data are about what we would expect. From the extrapolated data, it is impossible to see where the given data ends. For comparison, I prepared Figure 1.26. It is the same as Figure 1.25, except



Figure 1.25: Top is synthetic data with missing portions. Middle includes the interpolated values. Bottom is the filter, a *prediction-error* filter which may look symmetric but is not quite. mda-exp90 [ER]

that the filter is constrained in the middle. Notice that the extended data does *not* have the spectrum of the given data—the wavelength is much shorter. The boundary between real data and extended data is not nearly as well hidden as in Figure 1.25.



Figure 1.26: Top is the same synthetic data. Middle includes the interpolated values. Bottom is the filter, an *interpolation-error* filter. mda-center90 [ER]

1.8.2 Packing both missing data and filter into a vector

Now let us examine the theory and coding behind the above examples. Define a roughening filter $A(\omega)$ and a data signal $Y(\omega)$ at some stage of interpolation. The fitting goal is $0 \approx A(\omega)Y(\omega)$ where the filter $A(\omega)$ has at least one time-domain coefficient constrained to be nonzero and the data contains both known and missing values. Think of perturbations ΔA and ΔY. We neglect the nonlinear term $\Delta A\, \Delta Y$ as follows:

$$0 \approx (A + \Delta A)(Y + \Delta Y) \tag{1.33}$$

$$0 \approx A\,\Delta Y + Y\,\Delta A + AY + \Delta A\,\Delta Y \tag{1.34}$$

$$0 \approx A\,\Delta Y + Y\,\Delta A + AY \tag{1.35}$$

Linearizing a nonlinear fitting goal such as (1.35) seems reasonable. I linearized this way to first obtain the results of this chapter. Never-the-less, I find linearizing is a dangerous procedure that quickly leads to many problems. In reality, the term $\Delta A\, \Delta Y$ might not actually be small and the solution might not converge. You don't know how small is small, because these are not scalars but operators. The answer will depend on where you start from. Strange things happen. You can feel a sense of frustration. There is good news: Two stage linear least squares offers relief. You should first use linear least squares to get close to your answer. Generally, when finding the filter A we have plenty of regression equations, so we can afford to neglect the ones that depend upon unknown data. Then you can fix the filter and in a second stage, find the missing data. If you don't have enough regression equations because your data is irregularly distributed, then you can use binning. Still not enough? Try coarser bins. The point is that nonlinear solvers will not work unless you first get sufficiently close to the solution, and the way you get close is by arranging first to solve a sensible (though approximate) linearized problem. Only as a last resort, after you have gotten as near as you can, should you use the nonlinear least-squares techniques described below.

Let us use matrix algebraic notation to rewrite the fitting goals (1.35). For this we need mask matrices (diagonal matrices with ones on the diagonal where variables are free and zeros where they are constrained i.e., where $\Delta a_i = 0$ and $\Delta y_i = 0$). The free-mask matrix for missing data is denoted $\mathbf{J}$ and that for the PE filter is $\mathbf{K}$. The fitting goal (1.35) becomes

$$\mathbf{0} \approx \mathbf{AJ}\Delta\mathbf{y} + \mathbf{YK}\Delta\mathbf{a} + (\mathbf{Ay} \text{ or } \mathbf{Ya}) \tag{1.36}$$

or

$$\mathbf{0} \quad \approx \quad \begin{bmatrix} \mathbf{AJ} & \mathbf{YK} \end{bmatrix} \begin{bmatrix} \Delta\mathbf{y} \\ \Delta\mathbf{a} \end{bmatrix} + \mathbf{Ay} \tag{1.37}$$

For a 3-term filter and a 7-point data signal, the fitting goal (1.36) becomes

$$\begin{bmatrix}
a_0 & . & . & . & . & . & . & y_0 & . & . \\
a_1 & a_0 & . & . & . & . & . & y_1 & y_0 & . \\
a_2 & a_1 & a_0 & . & . & . & . & y_2 & y_1 & y_0 \\
. & a_2 & a_1 & a_0 & . & . & . & y_3 & y_2 & y_1 \\
. & . & a_2 & a_1 & a_0 & . & . & y_4 & y_3 & y_2 \\
. & . & . & a_2 & a_1 & a_0 & . & y_5 & y_4 & y_3 \\
. & . & . & . & a_2 & a_1 & a_0 & y_6 & y_5 & y_4 \\
. & . & . & . & . & a_2 & a_1 & . & y_6 & y_5 \\
. & . & . & . & . & . & a_2 & . & . & y_6 \\
. & . & . & . & . & . & . & . & . & .
\end{bmatrix}
\begin{bmatrix} \mathbf{J} & \mathbf{0} \\ \mathbf{0} & \mathbf{K} \end{bmatrix}
\begin{bmatrix} \Delta y_0 \\ \Delta y_1 \\ \Delta y_2 \\ \Delta y_3 \\ \Delta y_4 \\ \Delta y_5 \\ \Delta y_6 \\ \hline \Delta a_0 \\ \Delta a_1 \\ \Delta a_2 \end{bmatrix}
+
\begin{bmatrix} r_0 \\ r_1 \\ r_2 \\ r_3 \\ r_4 \\ r_5 \\ r_6 \\ r_7 \\ r_8 \\ 0 \end{bmatrix}
\approx \mathbf{0} \tag{1.38}$$

where $\mathbf{r} = \mathbf{Ay}$. In other words, r_t is the convolution of a_t with y_t, namely, $r_0 = y_0 a_0$ and $r_1 = y_0 a_1 + y_1 a_0$, etc. To optimize this fitting goal we first initialize $\mathbf{a} = (1, 0, 0, \cdots)$ and then put zeros in for missing data in $\mathbf{y}$. Then we iterate over equations (1.39) to (1.43).

$$\mathbf{r} \quad \longleftarrow \quad \mathbf{Ay} \tag{1.39}$$

$$\begin{bmatrix} \Delta\mathbf{y} \\ \Delta\mathbf{a} \end{bmatrix} \quad \longleftarrow \quad \begin{bmatrix} \mathbf{J}'\mathbf{A}' \\ \mathbf{K}'\mathbf{Y}' \end{bmatrix} \mathbf{r} \tag{1.40}$$

$$\Delta\mathbf{r} \quad \longleftarrow \quad \begin{bmatrix} \mathbf{AJ} & \mathbf{YK} \end{bmatrix} \begin{bmatrix} \Delta\mathbf{y} \\ \Delta\mathbf{a} \end{bmatrix} \tag{1.41}$$

$$\mathbf{y} \quad \longleftarrow \quad \text{cgstep}(\mathbf{y}, \Delta\mathbf{y}) \tag{1.42}$$

$$\mathbf{a} \quad \longleftarrow \quad \text{cgstep}(\mathbf{a}, \Delta\mathbf{a}) \tag{1.43}$$

This is the same idea as all the linear fitting goals we have been solving, except that now we recompute the residual $\mathbf{r}$ inside the iteration loop so that as convergence is achieved (*if* it is achieved), the neglected nonlinear term $\Delta A \Delta Y$ tends to zero.

I no longer exhibit the nonlinear solver `missif` until I find an example where it produces noticibly better results than multistage linear-least squares.

1.9 LEVELED INVERSE INTERPOLATION

Eighteenth- and nineteenth- century mathematics literature gives us many methods of interpolating functions. These classical methods are generally based on polynomials. The user specifies some order of polynomial and the theory works out the coefficients. Today our interest is in both interpolating and extrapolating wavefields (which are solutions to low order differential equations) and we use methods that are much better behaved than polynomials when extrapolating data, methods which behave acceptably when faced with contradictory data values, and methods which also apply in two and three dimensions.

In Chapter **??**, subroutine `invint1()` on page ?? solved the problem of inverse linear interpolation, which is, given scattered data points, to find a function on a uniform mesh from which linear interpolation gives the scattered data points. To cope with regions having no data points, the subroutine requires an input roughening filter. This is a bit like specifying a differential equation to be satisfied between the data points. The question is, how should we choose a roughening filter? The importance of the roughening filter grows as the data gets sparser or as the mesh is refined.

Figures 1.23-1.26 suggest that the choice of the roughening filter need not be subjective, nor a priori, but that the prediction-error filter (PEF) is the ideal roughening filter. Spectrally, the PEF tends to the inverse of its input hence its output tends to be "level". Missing data that is interpolated with this "leveler" tends to have the spectrum of given data.

1.9.1 Test results for leveled inverse interpolation

Figures 1.27 and 1.28 show the same example as in Figures **??** and **??**. What is new here is that the proper PEF is not given but is determined from the data. Figure 1.27 was made with a three-coefficient filter $(1, a_1, a_2)$ and Figure 1.28 was made with a five-coefficient filter $(1, a_1, a_2, a_3, a_4)$. The main difference in the figures is where the data is sparse. The data points in Figures **??**, 1.27 and 1.28 are samples from a sinusoid.



Figure 1.27: Interpolating with a three-term filter. The interpolated signal is fairly monofrequency. mda-subsine390 [ER,M]

Comparing Figures **??** and **??** to Figures 1.27 and 1.28 we conclude that by finding and imposing the prediction-error filter while finding the model space, we have interpolated beyond **aliasing** in data space.



Figure 1.28: Interpolating with a five term filter. mda-subsine590 [ER,M]

1.9.2 Analysis for leveled inverse interpolation

Here we see how the interpolation beyond aliasing was done. The first "statement of wishes" is that the observational data $\mathbf{d}$ should result from a linear interpolation $\mathbf{L}$ of the uniformly sampled model space $\mathbf{m}$; that is, $\mathbf{0} \approx \mathbf{Lm} - \mathbf{d}$. Expressing this as a change $\Delta\mathbf{m}$ gives the fitting goal in terms of the model change, $\mathbf{0} \approx \mathbf{L}\Delta\mathbf{m} + (\mathbf{Lm} - \mathbf{d}) = \mathbf{L}\Delta\mathbf{m} + \mathbf{r}$. The second wish is really an assertion that a good way to find missing parts of a function (the model space) is to solve for the function and its PEF at the same time. We are merging the fitting goal (**??**) for irregularly sampled data with the fitting goal (1.38) for finding the prediction-error filter.

$$\mathbf{0} \approx \mathbf{r}_d = \mathbf{L}\Delta\mathbf{m} + (\mathbf{Lm} - \mathbf{d}) \tag{1.44}$$

$$\mathbf{0} \approx \mathbf{r}_m = \mathbf{A}\Delta\mathbf{m} + \mathbf{MK}\Delta\mathbf{a} + (\mathbf{Am} \text{ or } \mathbf{Ma}) \tag{1.45}$$

Writing this out in full for 3 data points and 6 model values on a uniform mesh and a PEF of 3 terms, we have

$$\left[\begin{array}{cccccc|ccc}
.8 & .2 & . & . & . & . & & & \\
. & . & 1 & . & . & . & & & \\
. & . & . & . & .5 & .5 & & & \\
\hline
a_0 & . & . & . & . & . & m_0 & . & . \\
a_1 & a_0 & . & . & . & . & m_1 & m_0 & . \\
a_2 & a_1 & a_0 & . & . & . & m_2 & m_1 & m_0 \\
. & a_2 & a_1 & a_0 & . & . & m_3 & m_2 & m_1 \\
. & . & a_2 & a_1 & a_0 & . & m_4 & m_3 & m_2 \\
. & . & . & a_2 & a_1 & a_0 & m_5 & m_4 & m_3 \\
. & . & . & . & a_2 & a_1 & . & m_5 & m_4 \\
. & . & . & . & . & a_2 & . & . & m_5 \\
. & . & . & . & . & . & . & . & .
\end{array}\right]
\left[\begin{array}{cc} \mathbf{I} & \mathbf{0} \\ \mathbf{0} & \mathbf{K} \end{array}\right]
\left[\begin{array}{c} \Delta m_0 \\ \Delta m_1 \\ \Delta m_2 \\ \Delta m_3 \\ \Delta m_4 \\ \Delta m_5 \\ \Delta m_6 \\ \hline \Delta a_0 \\ \Delta a_1 \\ \Delta a_2 \end{array}\right]
+
\left[\begin{array}{c} r_{d0} \\ r_{d1} \\ r_{d2} \\ \hline r_{m0} \\ r_{m1} \\ r_{m2} \\ r_{m3} \\ r_{m4} \\ r_{m5} \\ r_{m6} \\ r_{m7} \end{array}\right]
\approx \mathbf{0} \tag{1.46}$$

where r_m is the convolution of the filter a_t and the model m_t, where r_d is the data misfit $\mathbf{r} = \mathbf{Lm} - \mathbf{d}$, and where $\mathbf{K}$ was defined in equation (1.11).

Before you begin to use this **nonlinear fitting goal**, you need some starting guesses for $\mathbf{m}$ and $\mathbf{a}$. The guess $\mathbf{m} = 0$ is satisfactory (as explained later). For the first guess of the filter, I suggest you load it up with $\mathbf{a} = (1, -2, 1)$ as I did for the examples here.

1.9.3 Seabeam: theory to practice

I provide here a more fundamental theory for dealing with the Seabeam data. I originally approached the data in this more fundamental way, but with time, I realized that I paid a high price in code complexity, computational speed, and reliability. The basic problem is that the elegant theory requires a good starting model which can only come from the linearized theory. I briefly recount the experience here, because the fundamental theory is interesting and because in other applications, you will face the challenge of sorting out the fundamental features from the essential features.

The linear-interpolation operator carries us from a uniform mesh to irregularly distributed data. Fundamentally we seek to solve the inverse problem to go the other direction. A nonlinear approach to filling in the missing data is suggested by the one-dimensional examples in Figures 1.27–1.28, where the PEF and the missing data are estimated simultaneously. The nonlinear approach has the advantage that it allows for completely arbitrary data positioning, whereas the two-stage linear approach forces the data to be on a uniform mesh and requires there not be too many empty mesh locations.

For the 2-D nonlinear problem, we follow the same approach we used in one dimension, equations (1.44) and (1.45), except that the filtering and the linear interpolations are two dimensional.

I have had considerable experience with this problem on this data set and I can report that bin filling is easier and works much more quickly and reliably. Eventually I realized that the best way to start the nonlinear iteration (1.44-1.45) is with the final result of bin filling. Then I learned that the extra complexity of the nonlinear iteration (1.44-1.45) offers little apparent improvement to the quality of the SeaBeam result. (This is not to say that we should not try more variations on the idea).

Not only did I find the binning method faster, but I found it to be *much* faster (compare a minute to an hour). The reasons for being faster (most important first) are,

1. Binning reduces the amount of data handled in each iteration by a factor of the average number of points per bin.

2. The 2-D linear interpolation operator adds many operations per data point.

3. Using two fitting goals seems to require more iterations.

(Parenthetically, I later found that helix preconditioning speeds the Seabeam interpolation from minutes to seconds.)

The most serious criticisim of the nonlinear approach is that it does not free us from the linearized approaches. We need them to get a "close enough" starting solution to the nonlinear problem. I learned that the iteration (1.44-1.45), like most nonlinear sequences, behaves unexpectedly and badly when you start too far from the desired solution. For example, I often began from the assumed PEF being a Laplacian and the original map being fit from that.

Oddly, from this starting location I sometimes found myself stuck. The iteration (1.44-1.45) would not move towards the map we humans consider a better one.

Having said all those bad things about iteration (1.44-1.45), I must hasten to add that with a different type of data set, you might find the results of (1.44-1.45) to be significantly better.

1.9.4 Risky ways to do nonlinear optimization

I have noticed that some geophysicists have adopted a risky method of nonlinear optimization, which is not advocated in the professional optimization literature. This risky method is to linearize a goal (with a multiparameter model space), then optimize the linearized goal, then relinearize, etc. The safer method is to relinearize after each step of CD.

An instructive example I learned about many years ago was earthquake epicenter location. Model space is latitude, longitude, and origin time. When people added a new variable, the depth, the solutions went wild until they learned to restrict the depth to zero until the other three parameters were stabilized. Apparently the instability stems from the fact that depth and origin time affect distant receivers in a similar way.

1.10 MULTIVARIATE SPECTRUM

A common **spectrum** is the Fourier spectrum. More fundamentally, a spectrum is a decomposition of a model space or data space into components. The components are in some sense independent; more specifically, the components are orthogonal to one another. Another well-known spectrum is provided by eigenvectors and eigenvalues. In statistical signal processing we handle a third type of spectrum, the multivariate spectrum.

Working in an optimization problem, we begin from residuals between theory and practice. These residuals can be scaled to make new optimization residuals before we start minimizing their energy. What scaling should we use? The scaling can be a simple weighting function or a filter. A filter is simply a weighting function in Fourier space.

The basic idea of common sense, which also comes to us as results proven by Gauss or from the theory of statistical signal processing, is this: The optimization residuals should be roughly of equal scale. This makes sense because squaring magnifies scale, and anything small will be ignored while anything large will dominate. Scaling optimization residuals to be in a common range makes them all equally influential on the final solution. Not only should optimization residuals be of like scale in physical space, they should be of like scale in Fourier space or eigenvector space, or any other space that we might use to represent the optimization residuals. This implies that the optimization residuals should be uncorrelated. If the optimization residuals were correlated, they would have a spectrum that was not white. Not white means of differing sizes in Fourier space. Residuals should be the same size as one another in physical space, likewise in Fourier space. Thus the optimization residuals should be orthogonal and of unit scale, much like Fourier components or as eigenvectors are

orthonormal.

Let us approach the problem backwards. Suppose we have two random variables that we take to be the ideal optimization residuals x_1 and x_2. In reality the two may be few or trillions. In the language of statistics, the optimization residuals are expected to have zero mean, an idea that is formalized by writing $E(x_1) = 0$ and $E(x_2) = 0$. Likewise these ideal optimization residuals have equal energy, $E(x_1^2) = 1$ and $E(x_2^2) = 1$. Finally, these two optimization residuals are uncorrelated, a condition which is written as $E(x_1 x_2) = 0$. The expectation symbol $E()$ is like a summation over many instances of the random variable.

Now suppose there exists a transformation $\mathbf{B}$ from these ideal optimization residuals to two experimental residuals y_1 and y_2, say $\mathbf{y} = \mathbf{B}\mathbf{x}$ where

$$\begin{bmatrix} y_1 \\ y_2 \end{bmatrix} = \begin{bmatrix} b_{11} & b_{12} \\ b_{21} & b_{22} \end{bmatrix} \begin{bmatrix} x_1 \\ x_2 \end{bmatrix} \tag{1.47}$$

The experimental residuals y_1 and y_2 are likely to be neither orthogonal nor equal in energy. From the column vector $\mathbf{y}$, the experimenter can form a square matrix. Let us also allow the experimenter to write the symbol $E()$ to denote summation over many trials or over many sections of data, ranges over time or space, over soundings or over receiver locations. The experimenter writes

$$\mathbf{R} = E(\mathbf{y}\mathbf{y}') \tag{1.48}$$
$$\mathbf{R} = E(\mathbf{B}\mathbf{x}\mathbf{x}'\mathbf{B}') \tag{1.49}$$

Given a random variable r, the expectation of $2r$ is simply $E(2r) = 2E(r)$. The $E()$ symbol is a summation on random variables, but constants like the coefficients of $\mathbf{B}$ pass right through it. Thus,

$$\mathbf{R} = \mathbf{B}\, E(\mathbf{x}\mathbf{x}')\, \mathbf{B}' \tag{1.50}$$
$$\mathbf{R} = \mathbf{B}\, E\left(\begin{bmatrix} x_1 \\ x_2 \end{bmatrix} \begin{bmatrix} x_1 & x_2 \end{bmatrix} \right) \mathbf{B}' \tag{1.51}$$
$$\mathbf{R} = \mathbf{B} \begin{bmatrix} E(x_1 x_1) & E(x_1 x_2) \\ E(x_2 x_1) & E(x_2 x_2) \end{bmatrix} \mathbf{B}' \tag{1.52}$$
$$\mathbf{R} = \mathbf{B}\mathbf{B}' \tag{1.53}$$

Given a matrix $\mathbf{R}$, there is a simple well-known method called the **Cholesky factorization** method that will factor $\mathbf{R}$ into two parts like $\mathbf{B}$ and $\mathbf{B}'$. The method creates for us either an upper or a lower triangular matrix (our choice) for $\mathbf{B}$. You can easily reinvent the Cholesky method if you multiply the symbols for two triangular matrices like $\mathbf{B}$ and $\mathbf{B}'$ and notice the procedure that works backwards from $\mathbf{R}$ to $\mathbf{B}$. The experimenter seeks not $\mathbf{B}$, however, but its inverse, the matrix that takes us from the experimental residuals to the ideal optimization residuals that are uncorrelated and of equal energies. The Cholesky factorization costs N^3 computations, which is about the same as the cost of the matrix inversion of $\mathbf{R}$ or $\mathbf{B}$. For geophysical maps and other functions on Cartesian spaces, the Prediction Error Filter (PEF) accomplishes the same general goal and has the advantage that we have already learned how to perform the operation using operators instead of matrices.

The multivariate spectrum of experimental residuals $\mathbf{y}$ is the matrix $\mathbf{R} = E(\mathbf{y}\mathbf{y}')$. For optimum model finding, the experimental residuals (squared) should be weighted inversely (matrix inverse) by their multivariate spectrum.

If I were a little stronger at analysis (or rhetoric) I would tell you that the optimizers preconditioned variable $\mathbf{p}$ is the statisticians IID (Independent Identically Distributed) random variable. For stationary (statistically constant) signals and images, $\mathbf{A}_m$ is the model-space PEF. Echo soundings and **interval velocity** have statistical properties that change with depth. There $\mathbf{A}_m$ is a diagonal weighting matrix (perhaps before or after a PEF).

1.10.1 What should we optimize?

Least-squares problems often present themselves as fitting goals:

$$\mathbf{0} \approx \mathbf{F}\mathbf{m} - \mathbf{d} \tag{1.54}$$
$$\mathbf{0} \approx \mathbf{m} \tag{1.55}$$

To balance our possibly contradictory goals we need weighting functions. The quadratic form that we should minimize is

$$\min_m \quad (\mathbf{F}\mathbf{m} - \mathbf{d})' \mathbf{A}_n' \mathbf{A}_n (\mathbf{F}\mathbf{m} - \mathbf{d}) + \mathbf{m}' \mathbf{A}_m' \mathbf{A}_m \mathbf{m} \tag{1.56}$$

where $\mathbf{A}_n' \mathbf{A}_n$ is the inverse multivariate spectrum of the noise (data-space residuals) and $\mathbf{A}_m' \mathbf{A}_m$ is the inverse multivariate spectrum of the model. In other words, $\mathbf{A}_n$ is a leveler on the data fitting error and $\mathbf{A}_m$ is a leveler on the model. There is a curious unresolved issue: What is the most suitable constant scaling ratio of $\mathbf{A}_n$ to $\mathbf{A}_m$?

1.10.2 Confusing terminology for data covariance

Confusion often stems from the mean of the data $E(\mathbf{d})$.

An experimentalist would naturally believe that the expectation of the data is solely a function of the data, that it can be estimated by averaging data.

On the other hand, a theoretician's idea of the expectation of the observational data $E(\mathbf{d})$ is that it is the theoretical data $\mathbf{F}\mathbf{m}$, that the expectation of the data $E(\mathbf{d}) = \mathbf{F}\mathbf{m}$ is a function of the model. The theoretician thinks this way because of the idea of noise $\mathbf{n} = \mathbf{F}\mathbf{m} - \mathbf{d}$ as having zero mean.

Seismological data is highly complex but also highly reproducible. In studies like seismology, the world is deterministic but more complicated than our ability to model. Thus, as a practical matter, the discrepancy between observational data and theoretical data is more realistically attributed to the theoretical data. It is not adequately modeled and computed.

This superficial difference in viewpoint becomes submerged to a more subtle level by statistical textbooks that usually define weighting functions in terms of variances instead of spectra. This is particularly confusing with the noise spectrum $\mathbf{A}_n'\mathbf{A}_n$. It is often referred to as the "**data covariance**" defined as $E[(\mathbf{d}-E(\mathbf{d}))(\mathbf{d}-E(\mathbf{d}))']$. Clearly, the noise spectrum is the same as the data covariance only if we accept the theoretician's definition that $E(\mathbf{d})=\mathbf{Fm}$.

There is no ambiguity and no argument if we drop the word "variance" and use the word "spectrum". Thus, (1) the "inverse **noise spectrum**" is the appropriate weighting for data-space residuals; and (2) the "inverse **model spectrum**" is the appropriate model-space weighting. Theoretical expositions generally require these spectra to be given as "**prior information**." In this book we see how, when the model space is a map, we can solve for the "prior information" along with everything else.

The statistical words "covariance matrix" are suggestive and appealing, but I propose not to use them because of the ambiguity of $E(\mathbf{d})$. For example, we understand that people who say "data covariance" intend the "multivariate noise spectrum" but we cannot understand their meaning of "model covariance". They should intend the "multivariate model spectrum" but that implies that $E(\mathbf{m})=\mathbf{0}$, which seems wrong. Avoiding the word "covariance" avoids the problem.

1.10.3 Hermeneutics

Hermeneutics is the study of the methodological principles of interpretation. Historically, it refers to biblical study. Never-the-less, it seems entirely appropriate for Geophysical Estimation. If Albert's book is "Inverse Problem Theory" and mine is "Inverse Problem Practice", and if the difference between theory and practice is smaller in theory than it is in practice, then there are two fundamental questions:

1. In theory, what is the difference between theory and practice? In theory, the difference is data error.

2. In practice, what is the difference between theory and practice? One suggestion is that the discrepancy is entirely due to inadequate modeling. It is well known that geophysical data is highly repeatable. The problem is that the modeling neglects far too much.

Index

aliasing, 32
autocorrelation, 10
autoregression, 1, 3

bound module, 17
Burg, 6

Cholesky factorization, 36
color, 6, 7
convolution
    two-dimensional, 8, 16

data covariance, 38
deconvolution, 5
dip-rejection filter, 9

FGDP, 6, 24
filter
    dip-rejection, 9
    interpolation-error, 4, 29
    multidimensional, 8
    prediction, 3
    prediction-error, 4, 18
    two-dimensional, 8, 9
    unknown, 27
fitting goal
    nonlinear, 33, 35
free-mask matrix, 4

hconest operator module, 14

interpolation
    beyond aliasing, 33
    inverse, 32
interpolation-error filter, 4, 29
interval velocity, 37
iteration count, 23

leveled inverse interpolation, 32
linear interpolation instead of binning, 34

mask matrix, 30
misinput module, 15
missing data, 23, 27, 30
model spectrum, 38
module
    `bound`, out of bounds dependency, 17
    `misinput`, mark bad regression equations, 15
    `pef`, estimate PEF on a helix, 19
multiple reflection, 2, 4

noise spectrum, 38
nonlinear fitting goal, 33
nonlinear optimization, 35

operator
    `hconest`, helix convolution, adjoint is the filter, 14
orthogonality, 7

PE filter, 6
PEF, 1, 6
pef module, 19
prediction filter, 3
prediction-error filter, 1, 4, 6, 18
prior information, 38

quarry blast, 23

reversing a signal, 24

seabeam, 25
soil, 7
source waveform, 2
spectrum, 27, 35
spectrum
    white 2-D, 11
stabilize, 2
Stanford University, 23

stationarity, 1
stationary, 29
symmetry in time, 24

time-series analysis, 1
two-dimensional filter, 9
two-stage
    least squares, 20
Two-stage linear least squares, 20

water bottom, 2
weighting function, 1
white, 7
white 2-D spectrum, 11
white spectrum, 6
whiteness
    multidimensional, 10